ALTERNATE PHASING ACTIVATION DETAIL

TO RUN ALT, PHASING DURING FREE RUN - PROGRAM CHANGES (SHOWN BELOW) IN A TIME BASED ACTION PLAN, SCHEDULE A DAY PLAN THAT INCLUDES THE ACTION PLAN PROGRAMMED TO SELECT VEH DET PLAN 2 AND ENABLE SF BITS 1 and 5.

TO RUN ALT, PHASING DURING COORDINATION - SELECT THE TIME BASED ACTION PLAN THAT IS PROGRAMMED

TO SELECT VEH DET PLAN 2 AND ENABLE SF BITS 1 and 5.

	H DET PLAN SF	BITS ENABLED
ACTIONS REQUIRED TO RUN <u>DEFAULT PHASING</u>	1	NONE
ACTIONS REQUIRED TO RUN <u>ALTERNATE PHASING</u>	2	1, 5

IMPORTANT: IF ALT. PHASING IS USED DURING FREE RUN AND COORDINATION, DO NOT OPERATE TIME OF DAY EVENTS CONCURRENTLY WITH COORDINATION PLAN EVENTS IN THE EVENT SCHEDULER. (EX. FREE RUN EVENT STARTS AND VICE-VERSA).

ALTERNATE PHASING CHANGE SUMMARY

THE FOLLOWING IS A SUMMARY OF WHAT TAKES PLACE WHEN SF BITS 1 AND 5 AND VEH DET PLAN 2 ACTIVATE TO CALL THE "ALTERNATE PHASING":

SF BITS 1.5: Modifies overlap parent phases for heads 11 and 51 to run

protected turns only.

protected turns only.

VEH DET PLAN 2: Disables phase 6 call on loop 1A and reduces delay time for phase 1

call on loop 1A to 0 seconds.


Disables phase 2 call on loop 5A and reduces delay time for phase 5 call on loop 5A to 0 seconds.

ECONOLITE ASC/3-2070 ACTION PLAN PROGRAMMING DETAIL

- 1. From Main Menu select 5. TIME BASE
- 2. From TIME BASE Submenu select 2. ACTION PLAN

ACTION PLA	٩N.	[1]														
PATTERN	SYS OVERRIDE NO																	
TIMING PLAN 0							SEQUENCE 0											
VEH DETECTOR PLAN 2							DET LOGNONE											
FLASH							RED REST NO											
VEH DET DIAG PLN O							PED DET DIAG PLNO											
DIMMING ENABLE NO						PR I	OR I	ΤΥ	RET	URN	. N	10						
PED PR RETURN NO						QUE	UE	DEL	AY.		. N	0						
PMT COND [DEL	ΑY		NO														
PHASE	1	2	3	4	5	6	7	8	9	0	1	2	3	4	5	6		
PED RCL	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•		
WALK 2	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•		
VEX 2	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•		
VEH RCL	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•		
MAX RCL	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•		
MAX 2	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•		
PHASE	1	2	3	4	5	6	7	8	9	0	1	2	3	4	5	6		
MAX 3	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•		
CS INH	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•		
OMIT	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•		
SPC FCT	Χ	•	•	•	X	•	•	•	(1	-8)								
AUX FCT	•	•	•	(1	-3)												
	1	2	3	4	5	6	7	8	9	0	1	2	3	4	5			
LP 1-15	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•			
LP 16-30	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•			
LP 31-45	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•			
LP 46-60	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•			
LP 61-75	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•			
LP 76-90	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•			
LP 91-100	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•			

THIS ELECTRICAL DETAIL IS FOR
THE SIGNAL DESIGN: 06-1224
DESIGNED: December 2015
SEALED: 8-24-16
REVISED: N/A



S:*ITS&SU*ITS Signals*Workgroups*Sig Man*Peterson*061224_sm_ele_xxx.c jtpeterson