

ECONOLITE ASC/3-2070 LOAD SWITCH ASSIGNMENT DETAIL

(program controller as shown)

To assign load switch S10 as OLE, program LD SWITCH 7 as OVLP '5' TYPE 'O' as shown below. To assign load switch S12 as Ped load switch 3, program LD SWITCH 16 as PHASE '3' TYPE 'P' as shown below.

1. From Main Menu select 1. CONFIGURATION
2. From CONFIGURATION Submenu select 3. LOAD SW ASSIGN

LD SWITCH ASSIGN							
	PHASE		DIMMING			---FLASH---	
	/OVLP	TYPE	R	Y	G	D	PWR AUT TGR
1	1	V	.	.	.	+	A R X
2	2	V	.	.	.	+	A Y .
3	3	V	.	.	.	+	A R X
4	4	V	.	.	.	+	A R .
5	5	V	.	.	.	-	A R .
6	6	V	.	.	.	-	A Y X
7	5	O	.	.	.	-	A R .
8	8	V	.	.	.	-	A R X
9	1	O	.	.	.	+	A R X
10	2	O	.	.	.	+	A R X
11	3	O	.	.	.	-	A R .
12	4	O	.	.	.	-	A R .
13	2	P	.	.	.	+	A . .
14	4	P	.	.	.	-	A . .
15	6	P	.	.	.	+	A . .
16	3	P	.	.	.	-	A . .



ECONOLITE ASC/3-2070 PED DETECTOR PROGRAMMING ASSIGNMENT DETAIL

(program controller as shown)

For Ped Detector 8 to call Phase 3 Ped.
program Ped Detector 8 as shown below.

1. From Main Menu select 6. DETECTORS
2. From DETECTOR Submenu select 3. PED DETECTOR INPUT ASSIGNMENT

PED DET PHASE ASSIGNMENT MODE: NTCIP								
PHASE	1	2	3	4	5	6	7	8
DETECTOR	0	2	8	4	0	6	0	0
PHASE	9	10	11	12	13	14	15	16
DETECTOR	0	0	0	0	0	0	0	0

← NOTICE PED DETECTOR 8.

THIS ELECTRICAL DETAIL IS FOR
THE SIGNAL DESIGN: 10-1732
DESIGNED: July 2017
SEALED: 9/25/2017
REVISED: N/A

Electrical Detail - Final Design - Sheet 2 of 2		DOCUMENT NOT CONSIDERED FINAL UNLESS ALL SIGNATURES COMPLETED						
<p style="font-size: small;">ELECTRICAL AND PROGRAMMING DETAILS FOR:</p> <p style="font-size: x-small;">Prepared In the Offices of:</p> <p style="font-size: x-small;">750 N. Greenfield Pkwy, Garner, NC 27529</p>	<p>SR 2894 (Concord Mills Blvd.) at Concord Mills Exit/ Shopping Center Entrance</p> <p style="font-size: x-small;">Division 10 Cabarrus County Concord</p> <p>PLAN DATE: September 2017 REVIEWED BY:</p> <p>PREPARED BY: S. Armstrong REVIEWED BY:</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <tr> <th style="width: 70%;">REVISIONS</th> <th style="width: 15%;">INIT.</th> <th style="width: 15%;">DATE</th> </tr> <tr> <td> </td> <td> </td> <td> </td> </tr> </table>	REVISIONS	INIT.	DATE				<p>SEAL</p> <p style="font-size: x-small;">DocuSigned by: Keith M. Mins 9/26/2017 2F8079E8C0D3445</p> <p style="font-size: x-small;">SIG. INVENTORY NO. 10-1732</p>
REVISIONS	INIT.	DATE						

26-SEP-2017 1:41:9
C:\PITS\SUM\T\S\SIGNAL\work\groups\Sig_Mobility\SigMgr\strongh01732-sm.ele.xxx.dgn
sarmstrong