


EDI MODEL 2018ECL-NC CONFLICT MONITOR PROGRAMMING DETAIL


(remove jumpers and set switches as shown)

REMOVE DIODE JUMPERS 1-5, 1-6, 1-9, 1-11, 1-17, 2-5, 2-6, 2-9, 2-11, 2-17, 2-18, 3-7, 3-8, 3-10, 3-12, 3-17, 3-18, 4-7, 4-8, 4-10, 4-11, 4-12, 4-17, 5-9, 5-11, 5-18, 6-9, 6-17, 6-18, 7-10, 7-11, 7-12, 7-17, 7-18, 8-10, 8-11, 8-12, 8-18, 9-11, 9-17, 9-18, 10-11, 10-12, 10-17, 10-18, 11-12, 11-17, 11-18, 12-17, 12-18, and 17-18.



REMOVE JUMPERS AS SHOWN

- NOTES:
- Card is provided with all diode jumpers in place. Removal of any jumper allows its channels to run concurrently.
 - Ensure jumpers SEL2-SEL5 and SEL9 are present on the monitor board.
 - Ensure that Red Enable is active at all times during normal operation.
 - Connect serial cable from conflict monitor to comm. port 1 of 2070 controller. Ensure conflict monitor communicates with 2070.



NOTES

- To prevent "flash-conflict" problems, insert red flash program blocks for all unused vehicle load switches in the output file. The installer shall verify that signal heads flash in accordance with the Signal Plans.
- Program phases 4 and 8 for Dual Entry.
- Enable Simultaneous Gap-Out for all Phases.
- Program phase 2 for Variable Initial and Gap Reduction.
- Program phases 2 and 6 for Startup In Green.
- Program phases 2 and 6 for Yellow Flash, and overlaps 1 and 2 as Wag Overlaps.
- If this signal will be managed by an ATMS software, enable controller and detector logging for all detectors used at this location.
- The cabinet and controller are part of the NC 133 Closed Loop System.

EQUIPMENT INFORMATION


CONTROLLER.....2070E
 CABINET.....332 W/AUX
 SOFTWARE.....ECONOLITE OASIS
 CABINET MOUNT.....BASE
 OUTPUT FILE POSITIONS...18 WITH AUX. OUTPUT FILE
 LOAD SWITCHES USED.....S1,S2,S4,S5,S7,S8,S10,S11,AUX S1,
 AUX S2,AUX S3,AUX S4,AUX S5,AUX S6
 PHASES USED.....1,2,3,4,5,6,7,8
 OVERLAP "A".....1+2
 OVERLAP "B".....3+4
 OVERLAP "C".....4+5
 OVERLAP "D".....7+8
 OVERLAP "E".....6+7
 OVERLAP "F".....2+3

SIGNAL HEAD HOOK-UP CHART

LOAD SWITCH NO.	S1	S2	S3	S4	S5	S6	S7	S8	S9	S10	S11	S12	AUX S1	AUX S2	AUX S3	AUX S4	AUX S5	AUX S6
CMU CHANNEL NO.	1	2	13	3	4	14	5	6	15	7	8	16	9	10	17	11	12	18
PHASE	1	2	2 PED	3	4	4 PED	5	6	6 PED	7	8	8 PED	OLA	OLB	OLE	OLC	OLD	OLF
SIGNAL HEAD NO.	11	21,22	NU	31	41,42	NU	51,52	61,62	NU	71	81,82	NU	11	31	63	43	71	23
RED		128		101		134		107							A111	A114		A104
YELLOW	*	129		* 102		135		* 108										
GREEN		130		103		136		109										
RED ARROW								131					A121	A124				A101
YELLOW ARROW								132					A122	A125	A112	A115	A102	A105
FLASHING YELLOW ARROW													A123	A126	A113	A116	A103	A106
GREEN ARROW	127			118		133				124								

NU = Not Used
 * Denotes install load resistor. See load resistor installation detail this sheet.
 ★ See pictorial of head wiring in detail this sheet.

INPUT FILE POSITION LAYOUT




EX.: 1A, 2A, ETC. = LOOP NO.'S
 FS = FLASH SENSE
 ST = STOP TIME
 ⊗ Wired Input - Do not populate slot with detector card

INPUT FILE CONNECTION & PROGRAMMING CHART

LOOP NO.	LOOP TERMINAL	INPUT FILE POS.	PIN NO.	INPUT ASSIGNMENT NO.	DETECTOR NO.	NEMA PHASE	CALL	EXTEND	FULL TIME DELAY	STRETCH TIME	DELAY TIME
ZONE 1A ¹	TB2-1,2	I1U	56	18	1	1	Y	Y			15
	-	J4U	48	10★	26	6	Y	Y			
	-	I1U	56	18★	51	1	Y	Y			
ZONE 3A ²	TB4-5,6	I5U	58	20	3	3	Y	Y			15
	-	J8U	50	12★	28	8	Y	Y			3
	-	I5U	58	20★	53	3	Y	Y			3
ZONE 7A ³	TB5-5,6	J5U	57	19	7	7	Y	Y			15
	-	I8U	49	11★	24	4	Y	Y			
	-	J5U	57	19★	57	7	Y	Y			


- Add jumper from I1-W to J4-W, on rear of input file.
 - Add jumper from I5-W to J8-W, on rear of input file.
 - Add jumper from J5-W to I8-W, on rear of input file.
- * See Input Page Assignment programming details on sheets 4, 5, and 6.

INPUT FILE POSITION LEGEND: J2L



FYA SIGNAL WIRING DETAIL

(wire signal heads as shown)




NOTE
 The sequence display for signal heads 11, 31, and 71 requires special logic programming. See sheet 2 for programming instructions.

LOAD RESISTOR INSTALLATION DETAIL

(install resistors as shown)

VALUE (ohms)	WATTAGE
1.5K - 1.9K	25W (min)
2.0K - 3.0K	10W (min)



! IMPORTANT: REMOVE RESISTOR FROM PHASE 5 RED FIELD TERMINAL, IF PRESENT.

SPECIAL DETECTOR NOTE

Install a microwave detection system for vehicle detection. Perform installation according to manufacturer's directions and NCDOT engineer-approved mounting locations to accomplish the detection schemes shown on the Signal Design Plans.

For loops 1A, 3A, and 7A, detector card placement and slots reserved for wired inputs are typical for a NCDOT installation. Inputs associated with these slots are compatible with time of day instructions located on sheets 4, 5, 6, and 7 of this electrical detail.

THIS ELECTRICAL DETAIL IS FOR THE SIGNAL DESIGN: 03-0215T6
 DESIGNED: June 2017
 SEALED: 9/10/2021
 REVISED: N/A

Electrical Detail - Sheet 1 of 9
 Signal Upgrade
 Temporary Design 6

DOCUMENT NOT CONSIDERED FINAL UNLESS ALL SIGNATURES COMPLETED

Prepared for:

NC 211 (Howe Street)
 at
 NC 87 (River Road)/
 SR 1852 (Robert Ruark Drive)
 Division 03 Brunswick Co. Southport

PLAN DATE: June 2017 REVIEWED BY: A.D. Klinskiak
 PREPARED BY: A.H. Thornburg REVIEWED BY: N.R. Simmons

SEAL

REVISIONS: _____ INITI. _____ DATE _____

9/10/2021
 SIGNATURE _____ DATE _____
 SIG. INVENTORY NO. 03-0215T6