ROJECT REFERENCE NO.	SHEET	ΓNO.
U - 4751	Sig	5.5

## ALTERNATE PHASING ACTIVATION DETAIL

TO RUN ALT. PHASING DURING COORDINATION — SELECT ALL PAGE CHANGES (AS SHOWN BELOW) WITHIN COORDINATION PLAN PROGRAMMING.

TO RUN ALT, PHASING DURING <u>free run</u> — program page changes (shown below) in separate time of day EVENTS. IF PAGE 1 IS USED, NO EVENT PROGRAMMING IS NECESSARY FOR THAT PARTICULAR PAGE.

PHASING	INPUTS PAGE	OVERLAPS PAGE
ACTIVE PAGES REQUIRED TO RUN <u>DEFAULT PHASING</u>	1	1
ACTIVE PAGES REQUIRED TO RUN <u>ALTERNATE PHASING</u>	2	2

NOTE: PAGES NOT SHOWN (i.e. sequence, phase control, etc.) SHOULD REMAIN AS '1', OR AS DEFINED BY TIMING ENGINEER.

IMPORTANT: IF ALT, PHASING IS USED DURING FREE RUN AND COORDINATION, DO NOT OPERATE TIME OF DAY PAGE CHANGE EVENTS CONCURRENTLY WITH COORDINATION PLAN EVENTS IN THE EVENT SCHEDULER. (EX. FREE RUN PAGE CHANGE EVENT SHOULD END BEFORE COORDINATION PLAN EVENT STARTS AND VICE-VERSA).

## ALTERNATE PHASING PAGE CHANGE SUMMARY

THE FOLLOWING IS A SUMMARY OF WHAT TAKES PLACE WHEN THESE OVERLAP/INPUT PAGE CHANGES ACTIVATE TO CALL THE "ALTERNATE PHASING":

OVERLAPS PAGE 2: Modifies overlap parent phases

for heads 11 and 51 to run

protected turns only.

INPUTS PAGE 2: Disables phase 6 call on loop 1A and reduces delay time for phase 1

call on loop 1A to 0 seconds.


Disables phase 2 call on loop 5A and reduces delay time for phase 5 call on loop 5A to 0 seconds.

> THIS ELECTRICAL DETAIL IS FOR THE SIGNAL DESIGN: 03-0390T1 DESIGNED: Aprıl 2017 SEALED:

> > DOCUMENT NOT CONSIDERED FINAL UNLESS ALL SIGNATURES COMPLETED

Signal Upgrade - Temporary Design (Electrical Detail Sheet 5 of 5)

REVISIONS



## US 17 Business (Market Street)

SR 2048 (Gordon Road)

REVISED:

Division 03 New Hanover County Wilmington PLAN DATE: April 2017 REVIEWED BY: MB Toth PREPARED BY: AM Encarnacion Reviewed BY:

INIT. DATE

Melissa B. Toth SIG. INVENTORY NO. 03-0390T1

025892

ATKINS 1616 EAST MILLBROOK ROAD, SUITE 160 RALEIGH, NORTH CAROLINA 27609 (919) 876-6888 NCBEES #F-0326