

*NOTE FOR ALL OVERLAPS: Use Default values for Overlap 'PLUS' programming details

FROM MAIN MENU PRESS "1" CONTROLLER AND THEN "5" OVERLAPS



Type:NORMAL Grn: O Yel: 3.5 Red: 1.5



CHANNEL & I/O PROGRAMMING DETAIL FOR FYA OPERATION

(program controller as shown below)

This programming takes the output that drives a Flashing Yellow Arrow and makes it flash.

FROM MAIN MENU, KEYSTROKES 1-8

Channel & I/O 1.Chan 1-16 4.Chan+ 1-16 7.IO Logic 2.chan 17-24 5.chan+ 17-24 8.IO Viewer 3.Chan Parms 6.IO Parms 9.IO UserMap

PRESS THE RIGHT ARROW KEY UNTIL THE SCREEN AT RIGHT APPEARS

Chan.1...2...3...4...5...6...7...8 > Chan. 9... 10... 11... 12... 13... 14... 15... 16 Flash Yel..... Flash Yel..... Flash Grn. X X Inhibit Red Flash In Inhibit Red Flash In Olap Ovrd 0 0 0 0 0 0 0 Olap Ovrd 0 0 0 0 0 0 0

Program the controller as shown above.

CHANNEL & I/O PROGRAMMING COMPLETE

THIS ELECTRICAL DETAIL IS FOR THE SIGNAL DESIGN: Ø7-1689T2 REVISED:

PROJECT REFERENCE NO.

U-4015A

| Sig. 6.2

Signal Upgrade - Temporary Design 2 (TMP Phase I Step 3) - Electrical Detail - Sheet 2 of 2 DOCUMENT NOT CONSIDERED FINAL UNLESS ALL SIGNATURES COMPLETED

ELECTRICAL AND PROGRAMMING SR 1556 (Gallimore Dairy Rd.) Prepared for the Offices of: SR 1554 (Chimney Rock Rd.)/

Simply Southern Division 7 Guilford County

PLAN DATE: August 2024 REVIEWED BY: DT Sears PREPARED BY: WP Erickson-Jones REVIEWED BY: REVISIONS

SEAL 7 056142

Porter Jones 8/22/2024 SIG. INVENTORY NO. 07-1689T2

RKK 8601 Six Forks Road Suite 700 | Raleigh, North Carolina 27615-2965 NC License No. F-0112 Engineers | Construction Managers | Planners | Scientists www.rkk.com

PRESS "ESC" TWICE

END OF OVERLAP PROGRAMMING DETAIL

DESIGNED: August 2024 SEALED: August 22,2024

Responsive People | Creative Solutions