

PROJECT REFERENCE NO.	SHEET NO.
U-5798B	Sig. 3.2

MAXTIME OVERLAP PROGRAMMING DETAIL FOR DEFAULT PHASING

Front Panel
Main Menu >Controller >Overlap >Overlap Parameters/Overlap Timings


Web Interface
Home >Controller >Overlap Configuration >Overlaps

Overlap Plan 1


Overlap	1	2	3	4	5	6
Type	FYA 4 - Section	FYA 4 - Section	Normal	FYA 4 - Section	FYA 4 - Section	FYA 4 - Section
Included Phases	8	4	1	8	6;7	2;3
Modifier Phases	1	3	-	7	-	-
Modifier Overlaps	-	-	-	-	-	-
Trail Green	0	0	0	0	0	0
Trail Yellow	0.0	0.0	0.0	0.0	0.0	0.0
Trail Red	0.0	0.0	0.0	0.0	0.0	0.0

FYA SIGNAL WIRING DETAIL


(wire signal heads as shown)




83, 84




31



71



63



23

MAXTIME OVERLAP PROGRAMMING DETAIL FOR ALTERNATE PHASING

Front Panel
Main Menu >Controller >Overlap >Overlap Parameters/Overlap Timings

Web Interface
Home >Controller >Overlap Configuration >Overlaps

In the table view of the web interface, right click on "Overlap" in the top left corner of the table. Copy the entire contents of Overlap Plan 1. Paste Overlap Plan 1 into Overlap Plan 2. Modify Overlap Plan 2 as shown below and save changes.

Overlap Plan 2

Overlap	1	2	3	4	5	6
Type	FYA 4 - Section	FYA 4 - Section	Normal	FYA 4 - Section	FYA 4 - Section	FYA 4 - Section
Included Phases	8	-	1	-	6; 7	2; 3
Modifier Phases	1	3	-	7	-	-
Modifier Overlaps	-	-	-	-	-	-
Trail Green	0	0	0	0	0	0
Trail Yellow	0:0	0:0	0:0	0:0	0:0	0:0
Trail Red	0:0	0:0	0:0	0:0	0:0	0:0

← NOTICE INCLUDED PHASE

MAXTIME STARTUP AND SOFTWARE FLASH PROGRAMMING DETAIL

Front Panel
Main Menu >Controller >Unit

Web Interface
Home >Controller >Unit

Modify parameters as shown below and save changes.

Start Up Parameters

StartUp Clearance Hold
6

Unit Flash Parameters

All Red Flash Exit Time
6

THIS ELECTRICAL DETAIL IS FOR
THE SIGNAL DESIGN: 06-1131T2
DESIGNED: June 2025
SEALED: 6/12/2025
REVISED:

Signal Upgrade - Temporary Signal 2
Electrical Detail - Sheet 2 of 3

<

\$\$\$\$SYTIME\$\$\$\$
\$\$\$\$\$\$\$\$DGN\$\$\$\$\$\$\$\$
\$\$\$\$\$USERNAME\$\$\$\$