

ECONOLITE ASC/3-2070 OVERLAP PROGRAMMING DETAIL

(program controller as shown)

1. From Main Menu select 2. CONTROLLER
2. From CONTROLLER Submenu select 2. VEHICLE OVERLAPS

OVERLAP A

Select TMG VEH OVLP [A] and 'PPLT FYA'

TMG VEH OVLP...[A] TYPE:PPLT FYA

PROTECTED LEFT TURN.... PHASE 1

OPPOSING THROUGH..... PHASE 2

FLASHING ARROW OUTPUT.....CH9 ISOLATE

DELAY START OF: FYA..0.0 CLEARANCE..0.0

ACTION PLAN SF BIT DISABLE..... 1

↓ Toggle Twice

OVERLAP C

Select TMG VEH OVLP [C] and 'PPLT FYA'

TMG VEH OVLP...[C] TYPE:PPLT FYA

PROTECTED LEFT TURN.... PHASE 5

OPPOSING THROUGH..... PHASE 6

FLASHING ARROW OUTPUT.....CH11 ISOLATE

DELAY START OF: FYA..0.0 CLEARANCE..0.0

ACTION PLAN SF BIT DISABLE..... 5

← NOTICE ACTION
PLAN SF BIT "1"

← NOTICE ACTION
PLAN SF BIT "5"



END PROGRAMMING

COUNTDOWN PEDESTRIAN SIGNAL OPERATION

Countdown Ped Signals are required to display timing only during Ped Clearance Interval. Consult Ped Signal Module user's manual for instructions on selecting this feature.

THIS ELECTRICAL DETAIL IS FOR
 THE SIGNAL DESIGN: 06-1280
 DESIGNED: August 2016
 SEALED: 10/15/2016
 REVISED: N/A

17-007-2016-09-16
 S:\IT\ASST\TS\Sigal\work\pgr\061280_sm.ele.xxx.dgn
 sarmstrong

Electrical Detail - Sheet 2 of 4		DOCUMENT NOT CONSIDERED FINAL UNLESS ALL SIGNATURES COMPLETED						
ELECTRICAL AND PROGRAMMING DETAILS FOR:  750 N. Greenfield Pkwy, Garner, NC 27529	US 401 (Ramsey Street) at Meadowcroft Drive/ North Walmart Entrance Division 6 Cumberland County Fayetteville PLAN DATE: October 2016 REVIEWED BY: BAS PREPARED BY: S. Armstrong REVIEWED BY:	SEAL  Documented by: Keith M. Mims 10/28/2016 DATE SIG. INVENTORY NO. 06-1280						
<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="width: 80%;">REVISIONS</th> <th style="width: 10%;">INIT.</th> <th style="width: 10%;">DATE</th> </tr> </thead> <tbody> <tr> <td> </td> <td> </td> <td> </td> </tr> </tbody> </table>			REVISIONS	INIT.	DATE			
REVISIONS	INIT.	DATE						