# MATIME OVERLAP PROGRAMMING FOR DEFAULT PHASING

Front Panel

Main Menu > Controller > Overlap > Overlap Parameters / Overlap Timings

Web Interface

Home >Controller >Overlap Configuration >Overlaps

Overlap Plan 1

Overlap	1	2	3	4
Type	FYA 4 - Section			
Included Phases	2	4	6	8
Modifier Phases	1	3	5	7
Modifier Overlaps	-		-	-
Trail Green	0	0	0	0
Trail Yellow	0.0	0.0	0.0	0.0
Trail Red	0.0	0.0	0.0	0.0

## MAXTIME OVERLAP PROGRAMMING DETAIL FOR ALTERNATE PHASING

Front Panel

Main Menu >Controller >Overlap >Overlap Parameters/Overlap Timings

Web Interface

Home >Controller >Overlap Configuration >Overlaps

In the table view of the web interface, right click on "Overlap" in the top left corner of the table. Copy the entire contents of Overlap Plan 1. Paste Overlap Plan 1 into Overlap Plan 2. Modify Overlap Plan 2 as shown below and save changes.

#### Overlap Plan 2

Overlap	1	2	3	4
Туре	FYA 4 - Section			
Included Phases	-	-	-	-
Modifier Phases	1	3	5	7
Modifier Overlaps	-		-	-
Trail Green	0	0	0	0
Trail Yellow	0.0	0.0	0.0	0.0
Trail Red	0.0	0.0	0.0	0.0

NOTICE INCLUDED PHASE

# MAXTIME ALTERNATE PHASING ACTIVATION DETAIL

To run alternate phasing, select a Pattern that is programmed to run Overlap Plan 2 and Detector Plan 2. A Pattern can be selected through the scheduler or manually by changing the Operational Mode.

PHASING	OVERLAP PLAN	VEH DET PLAN
ACTIVE PLAN REQUIRED TO RUN DEFAULT PHASING	1	1
ACTIVE PLAN REQUIRED TO RUN ALTERNATE PHASING	2	2

#### ALTERNATE PHASING CHANGE SUMMARY

THE FOLLOWING IS A SUMMARY OF WHAT TAKES PLACE WHEN OVERLAP PLAN 2 AND VEHICLE DETECTOR PLAN 2 ACTIVATE TO CALL THE "ALTERNATE PHASING":

OVERLAP PLAN 2: Modifies overlap included phases for heads 11, 31, 51, and 71 to

run protected turns only.

VEH DET PLAN 2: Disables phase 6 call on loop 1A and reduces delay time for phase 1

call on loop 1A to 3.0 seconds.

Disables phase 8 call on loop 3A and reduces delay time for phase 3 call on loop 3A to 0.0 seconds.

Disables phase 2 call on loop 5A and reduces delay time for phase 5 call on loop 5A to 3.0 seconds.

Disables phase 4 call on loop 7A and reduces delay time for phase 7 call on loop 7A to 3.0 seconds.

## MAXTIME ALTERNATE PHASING PATTERN PROGRAMMING DETAIL

Front Panel

Main Menu >Controller >Coordination >Patterns

Web Interface

Home >Controller >Coordination >Patterns

Pattern Parameters

Pattern	Veh Det Plan	Overlap Plan
*	2	2

\* The Pattern number(s) are to be determined by the Division Traffic Engineer.

## MAXTIME DETECTOR PROGRAMMING DETAIL FOR ALTERNATE PHASING LOOPS 1A, 3A, 5A & 7A

Front Panel

Main Menu >Controller >Detector >Veh Det Plans

Web Interface

Home >Controller >Detector Configuration >Vehicle Detectors

PROJECT REFERENCE NO.

U-5824

Sig. 13.2

In the table view of web interface right click on "Detector" in the top left corner of the table. Copy the entire contents of Detector Plan 1. Paste Detector Plan 1 into Detector Plan 2. Modify Detector Plan 2 as shown below and save changes.

Plan 2

1 1411 2		
Detector	Call Phase	Delay
1	1	3.0
29	0	3.0

	Detector	Call Phase	Delay
8A	7	3	0.0
	30	0	0.0

	Detector	Call Phase	Delay
5A	15	5	3.0
	31	0	3.0

	Detector	Call Phase	Delay
4	21	7	3.0
	32	0	3.0

## FLASHER CIRCUIT MODIFICATION DETAIL

IN ORDER TO ENSURE THAT SIGNALS FLASH CONCURRENTLY ON THE SAME APPROACH, MAKE THE FOLLOWING FLASHER CIRCUIT CHANGES:

- 1. ON REAR OF PDA REMOVE WIRE FROM TERM. T2-4 AND TERMINATE ON T2-2.
- 2. ON REAR OF PDA REMOVE WIRE FROM TERM. T2-5 AND TERMINATE ON T2-3.
- 3. REMOVE FLASHER UNIT 2.

THE CHANGES LISTED ABOVE TIES ALL PHASES AND OVERLAPS TO FLASHER UNIT 1.

### COUNTDOWN PEDESTRIAN SIGNAL OPERATION

Countdown Ped Signals are required to display timing only during Ped Clearance Interval. Consult Ped Signal Module user's manual for instructions on selecting this feature.

Electrical Detail - Final Design - Sheet 2 of 2

ELECTRICAL AND PROGRAMMIN

750 N.Greenfield Pkwy.Garner.NC 27529

NC 66 (Old Hollow Road) SR 2385 (Darrow Road)

Forsyth County REVIEWED BY: E. Sirgany PLAN DATE: August 2023 PREPARED BY: J. Smith REVIEWED BY: REVISIONS INIT. DATE

Edward W Sirgany 9/7/2023 SIG. INVENTORY NO. 09-0654

FINAL UNLESS ALL SIGNATURES COMPLETED

018174

THIS ELECTRICAL DETAIL IS FOR THE SIGNAL DESIGN: 09-0654 DESIGNED: August 2023 SEALED: 9/7/2023 504 Meadowlands Drive REVISED: N/A

Prepared in the Office of:

NC FIRM LICENSE No: P-0339 Hillsborough, NC 27278 (919) 732–3883 (919) 732–6676 (FAX)