

	_	<u>FNASING</u>							TABLE 0	F OPERATION						00701		DETEAT			
						<.				PHASE					UASIS		LUUP &		OR IN	OR PE	
		Ň							SIGNAL Ø		F							<u>ہے</u>			
									FACE		A S				LOOP	SIZE	FROM TU		HASE SU	ME DE	
									5	6 5 6	H					(FT)	(FT)	NEW	CA	EXTE	
									11 -		− R				1 A	6X60	+5 2-	4-2 -	1 Y	<u> </u>	
									21, 22 R	R G G G R					2:A	6X6	420	5 -	2 Y	Y -	
			Ø9	Y					41, 42 R						2B	6X6	420	5 -	2 Y	Y -	
	T		luring						51 -						4 A	6X60	+5 2-	4-2 -	4 Y	Y -	
									61 R						4B	6X15	+5	3 -	4 Y	Y -	
	► 8	*													5A	6X60	+5 2-	4-2 - 5	79 Y	Y -	
									STONAL						6B	626	420	5 -		Y _	
	Ø2+6	Ť							SIGNAL	FACE I.D.						0//0	120	5			
									All Hea	ids L.E.D.											
						r			(\mathbf{R}) (\mathbf{R})	(R)											
											INDUST	RIAL VENTUR	RES								
	Ø2+5				014	¥					7 12″										
					U T				(\bigcirc) (G)	(G) (-	\rightarrow										
											<u></u>		\sim								
									11 21, 22	62											
									51 41, 42 61												
									01			ade 									
	Ø1+6											0 1 1									
												+ [←]	S //								
Note: Note: <td< th=""><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th>H H H</th><th></th><th></th><th></th><th>Truck</th><th>$S + \alpha \rho$</th><th></th><th></th><th></th></td<>												H H H				Truck	$S + \alpha \rho$				
Public E13844 00ETT LIGBS Public E13844 00ETT VICENE Public E13840 00ETT VICENE Public E13840 00ETT VICENE VICENE VICENE		•										32 M	// Cha			HUCK	310P				
OASIS 2070L TIMING CHART State Annual Isad-In Textorial isad 1 2 1 2 1							PHASIN	<u>G DIAGRAM DETE</u>	CTION LEGEND												
		Ø1+5	/				~ •	DETECTED MOVE			•		23(`~===	====				Aeria	l lea	
US 74 US 74 <td< th=""><th></th><th></th><th></th><th></th><th></th><th>· · · ·</th><th>∢</th><th>UNDETECTED MC</th><th>MOVEMENT (UVERLAP)</th><th></th><th></th><th></th><th>∭ es ↓ €↓</th><th></th><th></th><th></th><th></th><th>11</th><th></th><th></th></td<>						· · · ·	∢	UNDETECTED MC	MOVEMENT (UVERLAP)				∭ es ↓ €↓					11			
US 74 1 <th></th> <th></th> <th>Li</th> <th></th> <th></th> <th><</th> <th>\in></th> <th>PEDESTRIAN MC</th> <th>VEMENT</th> <th>Gravel</th> <th>Drive</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th>			Li			<	\in >	PEDESTRIAN MC	VEMENT	Gravel	Drive										
				、									+						55	5 MPH	
Acrist lead-b The State 1 1			i)					US	5 74					· - - 							
Start 1 <th></th> <th>/</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th>/</th> <th>•</th> <th>→62</th> <th></th> <th></th> <th></th> <th></th> <th><</th> <th></th> <th></th> <th></th>		/								/	•	→62					<				
Stand Provide Ling 1												→ 61					←			_	
Arrival Load in 65 MPH +1% Brade Arrival Load in Testing Control 1 2 4 1 5 MPH +1% Brade Arrival Load in Testing Control 1 1 2 1 2 1 2 1 2 1 2 1 2 1 2 1 2 1 2 1 2 2 3 2 3 2 3 2 3 2 3 2 3 2 3 2 3 2 3 2 3 2 3 2 3 2 3 2 3 3 3 3 3 3 3 3 3 3 3 3 3												▼ 11			(1 A)		~			-	
Signal Phile Signal Phile <td< th=""><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th>)</th><th>)</th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th></td<>))									
Example Action Image: State Action								\wedge		<u> </u>			51 -								
So NPH +1% Grado Agrial lead-in Name Gradow Colspan="2">Agrial lead-in Agrial lead-in The base decimation 1								\rightarrow					21 -							<u> </u>	
St MPH +1% Grade Aprial lead-in CASIS 2070L TIMING CHART Min Green 1 2 4 5 6 9 0 (2 + 7) (0 + 5) Min Green 1 2 3 5 9 10 0 (2 + 7) (0 + 5) 0 (2 + 7) (0 + 5) Min Green 1 2 3 5 4 0 0 (2 + 7) (0 + 5) 0 (2 + 7) (0 + 5) Min Green 1 2 5 5 5 5 5 5 5 5 5 5 6 5 5 6 7 6 Min Green 1 2 3 2 3 <t< th=""><th></th><th>(2B) []</th><th></th><th></th><th></th><th></th><th></th><th>\longrightarrow</th><th></th><th></th><th></th><th></th><th>22 🔫</th><th></th><th></th><th></th><th>_</th><th></th><th></th><th></th></t<>		(2B) []						$ \longrightarrow $					22 🔫				_				
SJ Mri Tis Grade SJ Mri Tis Grade Arrial lead-in Arrial lead-in Arrial lead-in Mai Count 1 Z 4 9 Osis (p 10) Osis (p 10) Arrial lead-in Mai Count 1 Z 4 9 Osis (p 10) Osis (p 10) Arrial lead-in Mai Count 1 Z 4 9 Osis (p 10) Osis (p 10) Arrial lead-in Mai Count 1 Z 4 9 Osis (p 10) Osis (p 10) Arrial lead-in Mai Count 1 Z 4 9 Osis (p 10) Osis (p 10) Arrial lead-in Mai Count 1 Z 0 5.0 2.0 2.0 5.0 2					·																
Arial lead-in PHASE FEATURE 1 2 4 6 9 OLE 12-91 OP 19 19 Min Grea 1' 1/2 4 6 9 OLE 12-91 OP 19 19 10 Min Grea 1' 1/2 4 6 9 OLE 12-91 OP 19 19 10 Min Grea 1' 1/2 1/4	–					55	MPH +1%	Grade													
Acrial lead-in Acria Lead-in Acria Lead-in Acria Lead-in Acria Lead-in Acria Lead-in Acria Lead-in <th colspand<="" th=""><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th> </th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th></th>	<th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th> <th> </th> <th></th>																				
Actial lead-in Fature Image: Im																					
Vector Vector<					ттмтыс		•		—Aerial l	ead-in											
FATURE Image: construction of the state in			UA212 2	2070L																	
In transmit I <thi< th=""> I <thi< th=""><th>FFATURE</th><th>1</th><th>2</th><th>4</th><th>5</th><th>6</th><th>9</th><th>OIE [2+9] OIE [5+1]</th><th>- 91</th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th></thi<></thi<>	FFATURE	1	2	4	5	6	9	OIE [2+9] OIE [5+1]	- 91												
Eternion 1* 2.0 6.0 2.0 2.0 2.0 Max Gene 1* 3.2 900 6.0 3.0 1.5 Valion Gene no. 3.0 5.2 3.0 5.2 3.0 Red Charmone 3.6 5.2 3.0 2.6 3.3 2.6 3.0 Red Charmone 3.0 2.0	Min Green 1 *	7	14	7	7	14	7														
Max Green 1* 1b 90 20 1b 90 1c Image: Clearance 3.0 5.2 3.4 3.0 5.2 3.4 3.0 5.2 3.4 3.0 5.2 3.6 Red Clearance 3.6 1.3 2.3 2.0 3.6<	Extension 1 *	2.0	6.0	2.0	2.0	6.0	2.0														
Vellaw Clearance 3.0 5.2 3.6 3.0 9.3 3.0 5.2 3.0 Red Clearance 3.6 1.3 2.9 2.6 1.3 2.6 1.3 2.6 Red Revert 2.0	Max Green 1 *	15	90	30	15	90	15														
Red Clorence 3.6 1.3 2.6 1.3 2.6 1.3 2.6 Red Revert 2.0<	Yellow Clearance	3.0	5.2	3.5	3.0	5.3	3.0	5.2 3.0													
Red Roort 2.0	Red Clearance	3.6	1.3	2.9	2.6	1.3	2.6	1.3 2.6	_												
run 1 - <th>Red Revert</th> <th>2.0</th> <th>2.0</th> <th>2.0</th> <th>2.0</th> <th>2.0</th> <th>2.6</th> <th></th>	Red Revert	2.0	2.0	2.0	2.0	2.0	2.6														
Seconds Per Actuation 1.5 1.5 Max Variable Initial* 46 46 Max Variable Initial* 15 46 Time Before Roduction* 15 Minimum Gap 3.0 Minimum Gap 3.4 Vehide Call Memory Simultaneous Gap 0N 0N 0N 0N 0N 0N Vehides adjusted. Do not adjust Min Green and Extension times for basic 2 and 6 lower than whot	Don't Walk 1	_	_		-																
Max Variable Initial* 46 Max Variable Initial* 46 Time Before Reduction * 15 Time Defore Reduction * 15 Time Defore Reduction * 30 30 Time To Reduce * 30. 30. Minimum Gap 3.4 Vehicle Call Memory YELLOW Simultaneous Gap ON ON ON ON ON ON ON * These values may be field adjusted. Do not adjust Min Green and Extension times for phases 2 and 6 lower than what	Seconds Per Actuation *	-	1.5	_	-	1.5	_													C ; ~	
Time Before Reduction * - 15 - Time To Reduce * - 30 - 30 - Time To Reduce * - 30 - 30 - Minimum Gap - 3.4 - - Becal Mode - MIN RECALL - Vehicle Call Memory - YELLOW - YELLOW - - Joul Entry - - - - - - Simultaneous Gap ON ON ON ON ON ON ON * These values may be field adjusted. Do not adjust Min Green and Exterion times for phases 2 and 6 lower than what - - - -	Max Variable Initial *	-	46	-	-	46	-												1	o⊥g 	
Time To Reduce * - 30 - 30 - Minimum Gop - 3.4 - 3.4 - Minimum Gop - 3.4 - 3.4 - Recall Mode - MIN RECALL - MIN RECALL - Vehicle Call Memory - YELLOW - - YELLOW - Dual Entry - - - - - - - Simultaneous Gop ON ON ON ON ON ON ON ON * These values may be field adjusted. Do not adjust Min Green and Extension times for phases 2 and 6 lower than what	Time Before Reduction *	-	15	_	_	15	-													P	
Minimum Gap - 3.4 - - 3.4 - Recall Mode - MIN RECALL - MIN RECALL - Image: Comparison of the comparison of th	Time To Reduce *	-	30	_	_	30	-									NO					
Recall Mode - MIN RECALL - MIN RECALL - Vehicle Call Memory - YELLOW - YELLOW - Dual Entry - - YELLOW - - MIN RECALL - Simultaneous Gap ON ON ON ON ON ON ON ON * These values may be field adjusted. Do not adjust Min Green and Extension times for phases 2 and 6 lower than what Owner than what Owner than what	Minimum Gap	-	3.4	-	-	3.4	-								PLA	NS PR	EPAREL	ו <i>BY:</i>			
Venice can memory Itel off Itel off Dual Entry - - - - Dual Entry - - - - - Simultaneous Gap ON ON ON ON ON ON ON * These values may be field adjusted. Do not adjust Min Green and Extension times for phases 2 and 6 lower than what Item of the second	Recall Mode	-	MIN RECALL	_	-	MIN RECALL	-														
Simultaneous Gap ON ON ON ON ON Simultaneous Gap ON ON ON ON ON ON * These values may be field adjusted. Do not adjust Min Green and Extension times for phases 2 and 6 lower than what For N.G. For N.G.	Dual Entry	_		_	-																
* These values may be field adjusted. Do not adjust Min Green and Extension times for phases 2 and 6 lower than what	Simultaneous Gap	ON	ON	ON	ON	ON	ON									NGINEERS	• PLANNEF	RS · SCIENT	ISTS	750 N.G	
	* These values may be field	ı d adjusted. Do	not adjust Min G	reen and Exte	ension times for	phases 2 and 6	lower than whe	at								DRI 5950 FAIRVIEV	MP, INC. V ROAD, SUITE	320			

* These values may be field adjusted. Do not adjust Min Green and Extension times for phases 2 and 6 lower than what is shown. Min Green for all other phases should not be lower than 4 seconds.



NC LICENSE NO. C-2213 • (704) 332-2289

1″=40′

PROJECT REFERENCE NO.

SIG. INVENTORY NO. |0-|505

W-5520

SHEET NO.

Sig. 27.0