EMERGENCY VEHICLE PREEMPTION
PROGRAMMING DETAIL

(program controller as shown below)

From Main Menu press 'A' (Preemption), then '1'
(Standard Preemptions). Press 'NEXT' to advance
to Preemption #3 and 5.

```
   PREEMPTION  #3  SETTINGS (NEXT:1-10)
 INTERVAL/TIMING ¦  CLEAR/DWELL PHASES
  GRN YEL  RED   ¦12345678910111213141516
1 255  0.0  0.0 ¦X    X
2   0  0.0  0.0 ¦
3   0  0.0  0.0 ¦
4   0  0.0  0.0 ¦
5   0  0.0  0.0 ¦
EXIT CALLS       ¦
         OPTIONS
PRIORITY (Y/N TO SELECT) ............MED
DELAY TIMER (0-255 SEC) .............0
MIN GREEN BEFORE PRE (0= DEFAULT)....1
PED CLEAR BEFORE PRE (0= DEFAULT)....0
YELLOW CLEAR BEFORE PRE (0= DEFAULT).0.0
RED CLEAR BEFORE PRE (0= DEFAULT)....0.0
DWELL MIN TIMER (0-255 SEC) .........12
DWELL MAX TIMER (0=OFF,1-255MIN) ....0
DWELL HOLD-OVER TIMER (0-255) .......0
LATCH CALL? .........................N
LINK TO NEXT PREEMPT? ...............N
ENABLE BACKUP PROTECTION? ...........N
HOLD CLEAR 1 PHASES DURING DELAY? ...N
FAST GREEN FLASH DWELL PHASES? ......N
PED CLEARANCE THROUGH YELLOW? .......N
INHIBIT OVERLAP GREEN EXTENSION? ....N
SERVICE DURING SOFTWARE FLASH? ......N
REST IN RED DURING DWELL INTERVAL? ..N
FLASH DWELL INTERVAL? ...............N
ALLOW PEDS IN DWELL INTERVAL? .......N
RE-TIME DWELL INTERVAL? .............N
OVERLAPS:        ¦ ABCDEFGHIJKLMNOP
DWELL INT FLASH YELLOW
OMIT OVERLAPS:   ¦
```

```
   PREEMPTION  #5  SETTINGS (NEXT:1-10)
 INTERVAL/TIMING ¦  CLEAR/DWELL PHASES
  GRN YEL  RED   ¦12345678910111213141516
1 255  0.0  0.0 ¦X    X
2   0  0.0  0.0 ¦
3   0  0.0  0.0 ¦
4   0  0.0  0.0 ¦
5   0  0.0  0.0 ¦
EXIT CALLS       ¦
         OPTIONS
PRIORITY (Y/N TO SELECT) ............MED
DELAY TIMER (0-255 SEC) .............0
MIN GREEN BEFORE PRE (0= DEFAULT)....1
PED CLEAR BEFORE PRE (0= DEFAULT)....0
YELLOW CLEAR BEFORE PRE (0= DEFAULT).0.0
RED CLEAR BEFORE PRE (0= DEFAULT)....0.0
DWELL MIN TIMER (0-255 SEC) .........12
DWELL MAX TIMER (0=OFF,1-255MIN) ....0
DWELL HOLD-OVER TIMER (0-255) .......0
LATCH CALL? .........................N
LINK TO NEXT PREEMPT? ...............N
ENABLE BACKUP PROTECTION? ...........N
HOLD CLEAR 1 PHASES DURING DELAY? ...N
FAST GREEN FLASH DWELL PHASES? ......N
PED CLEARANCE THROUGH YELLOW? .......N
INHIBIT OVERLAP GREEN EXTENSION? ....N
SERVICE DURING SOFTWARE FLASH? ......N
REST IN RED DURING DWELL INTERVAL? ..N
FLASH DWELL INTERVAL? ...............N
ALLOW PEDS IN DWELL INTERVAL? .......N
RE-TIME DWELL INTERVAL? .............N
OVERLAPS:        ¦ ABCDEFGHIJKLMNOP
DWELL INT FLASH YELLOW
OMIT OVERLAPS:   ¦      X
```

PRESS 'NEXT' TWICE

Program extend time
an optical detector
unit for 5.0 seconds.

THIS ELECTRICAL DETAIL IS FOR
THE SIGNAL DESIGN: 04-0802T1
DESIGNED: November 2016
SEALED: 1/30/2017
REVISED:

**DOCUMENT NOT CONSIDERED FINAL
UNLESS ALL SIGNATURES COMPLETED**

ELECTRICAL DETAIL SHEET 2 OF 2 - Temporary Design 1 (Area 3 TMP Phase I & II)

ELECTRICAL AND PROGRAMMING
DETAILS FOR:

Prepared for the Offices of:

US 301 Byp (N. Wesleyan Blvd)
at
Sutters Creek Blvd

Division 04	Nash County	Rocky Mount
PLAN DATE: November 2016	REVIEWED BY:	MB Toth
PREPARED BY: AM Encarnacion	REVIEWED BY:	

750 N.Greenfield Pkwy,Garner,NC 27529

REVISIONS	INIT.	DATE

SEAL

NORTH CAROLINA
PROFESSIONAL
SEAL
025892
ENGINEER
MELISSA B. TOTH

Developed by
Melissa B. Toth
1/30/2017
DATE

SIG. INVENTORY NO. 04-0802T1

ATKINS 1616 EAST MILLBROOK ROAD, SUITE 160
RALEIGH, NORTH CAROLINA 27609
(919) 876-6888   NCBEES #F-0326