OVERLAP PROGRAMMING DETAIL FOR DEFAULT PHASING

Front Panel

Main Menu >Controller >Overlap >Overlap Parameters/Overlap Timings

Web Interface

Home >Controller >Overlap Configuration >Overlaps

Overlap Plan 1

Overlap	1	2	3	4	7	8
Туре	Off	Off	FYA 4 - Section	FYA 4 - Section	Normal	Normal
Included Phases		·	6	4	5,7	4,7
Modifier Phases			5	·		
Modifier Overlaps	=	-	-	7		
Trail Green	0	0	0	0	0	0
Trail Yellow	0.0	0.0	0.0	0.0	0.0	0.0
Trail Red	0.0	0.0	0.0	0.0	0.0	0.0
FYA Ped Delay	0.0	0.0	0.0	6.0	0.0	0.0

MAXTIME OVERLAP PROGRAMMING DETAIL FOR ALTERNATE PHASING

Front Panel

Main Menu >Controller >Overlap >Overlap Parameters/Overlap Timings

Web Interface

Home >Controller >Overlap Configuration >Overlaps

In the table view of the web interface, right click on "Overlap" in the top left corner of the table. Copy the entire contents of Overlap Plan 1. Paste Overlap Plan 1 into Overlap Plan 2. Modify Overlap Plan 2 as shown below and save changes.

Overlap Plan 2

Overlap	1	2	3	4	7	8
Туре	Off	Off	FYA 4 - Section	FYA 4 - Section	Normal	Normal
Included Phases				4	5,7	4,7
Modifier Phases			5	·		
Modifier Overlaps	_	-	-	7		
Trail Green	0	0	0	0	0	0
Trail Yellow	0.0	0.0	0.0	0.0	0.0	0.0
Trail Red	0.0	0.0	0.0	0.0	0.0	0.0
FYA Ped Delay	0.0	0.0	0.0	6.0	0.0	0.0

MAXTIME ALTERNATE PHASING PATTERN PROGRAMMING DETAIL

Front Panel

Main Menu >Controller >Coordination >Patterns

Web Interface

Home >Controller >Coordination >Patterns

Pattern Parameters

Pattern	Veh Det Plan	Overlap Plan
*	2	2

*The Pattern number(s) are to be determined by the Division and/or City Traffic Engineer

VEHICLE DETECTOR PROGRAMMING DETAIL FOR ALTERNATE PHASING LOOP 5A

Front Panel

Main Menu >Controller >Detector >Veh Det Plans

Web Interface

Home >Controller >Detector Configuration >Vehicle Detectors

In the table view of web interface right click on "Detector" in the top left corner of the table. Copy the entire contents of Detector Plan 1. Paste Detector Plan 1 into Detector Plan 2. Modify Detector Plan 2 as shown below and save changes.

Plan 2

Detector	Call Phase	Delay	
15	5	0.0	
31	0	0.0	

PROJECT REFERENCE NO. Sig.14.2

OUTPUT CHANNEL CONFIGURATION

Front Panel

Main Menu >Controller >More>Channels>Channels Config

Web Interface

Home >Controller >Advanced IO>Channels>Channels Configuration

Channel Configuration

	Channel	Control Type	Control Source	Flash Yellow	Flash Red	Flash Alt	MMU Channel
	1	Phase Vehicle	1		X	X	1
	2	Phase Vehicle	2	Х			2
NOTE _	3	Phase Vehicle	3		Х	Х	3
CHANGE -	4	Overlap	8		Х	-	4
CHANGE	5	Phase Vehicle	5	·	Х	-	5
NOTE _	6	Phase Vehicle	6	Х		Χ	6
CHANGE -	7	Overlap	7		Х		7
CHANGE	8	Phase Vehicle	8		Х	Х	8
	9	Overlap	1	X		Χ	9
	10	Overlap	2		X	Χ	10
	11	Overlap	3	Х			11
	12	Overlap	4		Х	-	12
	13	Phase Ped	2			-	13
	14	Phase Ped	4				14
	15	Phase Ped	6			-	15
	16	Phase Ped	8			-	16
	17	Overlap	5		Χ	Χ	17
	18	Overlap	6		Х		18

MAXTIME ALTERNATE PHASING ACTIVATION DETAIL

To run alternate phasing, select a Pattern that is programmed to run Overlap Plan 2 and Detector Plan 2. A Pattern can be selected through the scheduler or manually by changing the Operational Mode.

PHASING	OVERLAP PLAN	VEH DET PLAN
ACTIVE PLAN REQUIRED TO RUN DEFAULT PHASING	1	1
ACTIVE PLAN REQUIRED TO RUN ALTERNATE PHASING	2	2

ALTERNATE PHASING CHANGE SUMMARY

THE FOLLOWING IS A SUMMARY OF WHAT TAKES PLACE WHEN OVERLAP PLAN 2 AND VEHICLE DETECTOR PLAN 2 ACTIVATE TO CALL THE "ALTERNATE PHASING":

OVERLAP PLAN 2: Modifies overlap included phases for head 51 to run protected turns only.

VEH DET PLAN 2: Disables phase 2 call on loop 5A and reduces delay time for phase 5 call on loop 5A to 0 seconds.

THIS ELECTRICAL DETAIL IS FOR

THE SIGNAL DESIGN: 09-0400

DESIGNED: May 2024

SEALED: 05-09-2024

REVISED: N/A

Electrical Detail - Sheet 2 of 3

Electrical and Programming Details For: Prepared for the Offices of:

NC 8 (Winston Road)

SR 1406 (Biesecker Road) Davidson County

PLAN DATE: May 2024 REVIEWED BY: J.T. Rowe REVIEWED BY: G.G. Murr, Jr

REVISIONS INIT.

SIG. INVENTORY NO. 09-0400

DOCUMENT NOT CONSIDERED

FINAL UNLESS ALL SIGNATURES COMPLETED

1 Glenwood Avenue

License: F-0453

NOTICE REMOVED INCLUDED PHASES